

According to a second aspect of the present invention the spectral values are grouped into spectral sections, a different code table being assigned to each of these spectral sections. The assignment of a code table to a spectral section is made according to signal statistical considerations, i.e. which code table is best suited for the coding of a spectral section. The assignment of a code table to a spectral section is already known in this branch of technology.

A raster will now be employed which consists of several groups of equidistant raster points such that the distance between the raster points of a group of raster points depends on the code table used for coding a spectral section. In another spectral section another code table is used so as to obtain an optimal data reduction. This other code table has a different group of equidistant raster points assigned to it, the distance between two raster points of this other group of raster points depending on the associated code table. The distance between two raster points in the different groups of raster points can be determined in at least three ways.

In the first the maximum length of a code word of a code table is ascertained. The separation of two raster points in the raster point group which is assigned to this code table can now be chosen to be equal to or greater than the maximum code word length in the code table, so that there is room in the raster for even the longest code word of this code table. The separation of two raster points of a different group of raster points, which are associated with a different code table, is determined in an analogous way according to the maximum code word length of this other code table.

The second alternative, which will now be described, can also contribute to an increase in the number of raster points. Be-

09869401-090501

cause of the inherent properties of the Huffman code, less frequently occurring code words tend to be longer than more frequently occurring code words. When the raster point separation is chosen to be equal to or greater than the length of the code word of maximum length in a table, therefore, the code words inserted in the raster are usually shorter than the raster point separation. The raster point separation can thus also be chosen to be smaller than the length of the longest code word of a table. If a code word which doesn't fit into the raster then appears when coding, the remainder which fails to fit into the raster is inserted into the bit stream at some other suitable position which is not aligned with the raster. As a consequence, this "cut-up" code word is no longer effectively protected against error propagation. Since this occurs very rarely, however, it can be accepted in the interests of an increase in the number of raster points.

The third possibility of determining the different raster point separations is to consider not the maximum code word length of a table but the length of the longest code word in a bit stream which actually occurs in a coded spectral section.

According to a third aspect of the present invention, instead of a code word arrangement in the bit stream which essentially increases linearly with the frequency, an arrangement in which the code words are distributed over the frequency spectrum can be used, a method which is also known as "scrambling". This has the advantage that so-called "burst errors" do not lead to erroneous decoding of a complete frequency band but simply to small disturbances in several different frequency ranges.

According to a fourth aspect of the present invention, instead of a code word arrangement which increases linearly with the frequency an arrangement can also be used in which e.g. only each n-th (e.g. each second, or third or fourth, ...) code

0969401.090501

word is arranged in the raster. In this way it is possible to span the greatest possible spectral region using priority code words, i.e. to protect against error propagation, when the number of possible raster points is less than the number of priority code words.

Furthermore, preference is given to determining the priority code words in such a way as to achieve efficient operation. Preferably this means abandoning the assumption that the psychoacoustically significant code words, i.e. the priority code words, are those which code the spectral values with low frequency. This will often be the case, but does not always have to be so.

Normally priority code words are code words which code psychoacoustically important spectral lines, these usually being spectral values with high energy. It is equally important that spectral lines with high energy do not arise because of errors.

According to the present invention an indicator is used which is already implicitly determined. The indicator depends on the code table which is used. In the AAC standard there are e.g. eleven code tables with different absolute value ranges. The code table No. 1 comprises e.g. spectral values having an absolute value from -1 to +1, while the code table No. 11 can code spectral values from -8191 to +8191. The higher the code table is the greater is the value range which it permits. This means that code tables with low numbers represent only relatively small values, and thus permit only relatively small errors, while code tables with higher numbers can represent relatively large values and thus also relatively large errors.

If an error occurs in a low code table it may well not be audible since an erroneous spectral line results which, seen ab-

09869401.090501